

UHF ANTENNA DIVERSITY SINGLE CHANNEL SYSTEM

SYSTEM FEATURES

- ※ UHF 800MHz operation frequency
- ※ Antenna diversity single channel operation.
- ※ Extreme low THD and super fidelity
- ※ Switch impact noise defeat circuit
- ※ Double squelch operation circuit, higher efficient and much more steady.
- ※ Balanced XLR and unbalanced 1/4" outputs.



PT-300
BODYPACK TRANSMITTER
Top View



WR-311
ANTENNA DIVERSITY RECEIVER

HT-300
HANDHELD TRANSMITTER

HT-15A
HANDHELD TRANSMITTER



19-inch Audio equipment rack



Rear Panel

WR-311 SERIES >>>

PROFESSIONAL WIRELESS MICROPHONE SYSTEM

WR-311



RECEIVER SPECIFICATIONS

- RF Frequency Range:460-970MHz
- Image & Squirous Rejection:>70dB
- Receiving Sensitivity:-105dBm
- Signal/Noise Ratio:-105dB
- Border Upon Channel Rejection>70dB
- T.H.D.:<1%
- Audio Output Level:0-300mV
- Power Requirements:13-15V DC nominal 300mA
- Dimensions:20.3x15x4cm

HT-300/HT-15A



HANDHELD TRANSMITTER SPECIFICATIONS

- RF Frequency Range:460-970MHz
- RF Output:10dBm
- Modulation Type:FM
- Max Deviation:±40KHz
- Spurious Emission:>55dBc
- Nominal Current Drain:<40mA
- Power Requirements:2x1.5V AA
- HT-300 Dimensions:25x5x5cm
- HT-15A Dimensions:25x5.1x5.1cm

PT-300



BODYPACK TRANSMITTER SPECIFICATIONS

- RF Frequency Range:460-970MHz
- RF Output:10dBm
- Modulation Type:FM
- Max Deviation:±40KHz
- Spurious Emission:>53dBc
- Nominal Current Drain:<40mA
- Power Requirements:2x1.5V AA
- Dimensions:10x6.2x2.2cm

HANDHELD

Receiver:WR-311
Handheld Mic:HT-300/HT-15A



LAVALIER

Receiver:WR-311
Bodypack Transmitter:PT-300
Lavalier Mic:LT-4A



HEADWORN

Receiver:WR-311
Bodypack Transmitter:PT-300
Headworn Mic: HT-9A



GUITAR/BASS

Receiver:WR-311
Bodyhack Transmitter:PT-300
Guitar Cable:G-05

