

UHF ANTENNA DIVERSITY SINGLE CHANNEL SYSTEM

SYSTEM FEATURES

- ※ UHF 800MHz operation frequency
- ※ Antenna diversity single channel operation.
- ※ Extreme low THD and super fidelity
- ※ Switch impact noise defeat circuit
- ※ Double squelch operation circuit, higher efficient and much more steady.
- ※ Balanced XLR and unbalanced 1/4" outputs.



KRU-317 SERIES >>>

PROFESSIONAL WIRELESS MICROPHONE SYSTEM

<p>KRU-317</p>	<p>KST-5U</p>	<p>KLT-8U</p>
<p>RECEIVER SPECIFICATIONS</p> <p>RF Frequency Range:460-970MHz Image & Scurious Rejection:>70dB Receiving Sensitivity:-105dBm Signal/Noise Ratio:-105dB Border Upon Channel Rejection>70dB T.H.D.:<1% Audio Output Level:0-300mV Power Requirements:13-15V DC nominal 300mA Dimensions:21.3x15x4.3cm</p>	<p>HANDHELD TRANSMITTER SPECIFICATIONS</p> <p>RF Frequency Range:460-970MHz RF Output:10dBm Modulation Type:FM Max Deviation: ± 40KHz Spurious Emission:>55dBc Nominal Current Drain:<40mA Power Requirements:9V DC Dimensions:20x21x4.9cm</p>	<p>BODYPACK TRANSMITTER SPECIFICATIONS</p> <p>RF Frequency Range:460-970MHz RF Output:10dBm Modulation Type:FM Max Deviation: ± 40KHz Spurious Emission:>53dBc Nominal Current Drain:<40mA Power Requirements:9V DC Dimensions:10.5x6.5x2.5cm</p>

<p>HANDHELD</p> <p>Receiver:KRU-317 Handheld Mic:KST-5U</p>	<p>LAVALIER</p> <p>Receiver:KRU-317 Bodypack Transmitter:KLT-8U Lavalier Mic:LT-4A</p>
<p>HEADWORN</p> <p>Receiver:KRU-317 Bodypack Transmitter:KLT-8U Headworn Mic: HT-9A</p>	<p>GUITAR/BASS</p> <p>Receiver:KRU-317 Bodypack Transmitter:KLT-8U Guitar Cable:G-05</p>