

VHF DUAL CHANNEL SYSTEM


KRV-202 SERIES >>> PROFESSIONAL WIRELESS MICROPHONE SYSTEM

SYSTEM FEATURES

- ※ VHF 200MHz operation frequency
- ※ Dual channel operation
- ※ Extreme low THD and super fidelity
- ※ Switch impact noise defeat circuit
- ※ Double squelch operation circuit, higher efficient and much more steady.
- ※ Balanced XLR and unbalanced 1/4" outputs.
- ※ EIA standard half rack metal housing with rack ear.



KLT-80V
BODYPACK TRANSMITTER



Top View




KRV-202
DUAL CHANNEL RECEIVER



KST-53V
HANDHELD TRANSMITTER



19-inch Audio equipment rack



Rear Panel

KRV-202	KST-53V	KLT-80V
RECEIVER SPECIFICATIONS Carrier Frequency: VHF 170-260MHz Power Requirements:13-15V DC nominal 300mA Signal/Noise Ratio: MORE THAN 90dB Image And Spurious Rejection: MORE THAN 80dB Border Upon Channel Rejection: MORE THAN 85dB Audio Output Level:0-300mV Receiving Sensitivity:-105dBm Dimensions:21x26.5x4.3cm	HANDHELD TRANSMITTER SPECIFICATIONS Power Requirement:9V Alkaline Battery Nominal Current Drain:LESS THAN 25mA Modulation Type:FM RF Output:MORE THAN13dBm Max Deviation:± 35KHz Spurious Emission:MORE THAN 55dB Dimensions:23.5x5x5cm	BODYPACK TRANSMITTER SPECIFICATIONS Power Requirement:9V Alkaline Battery Nominal Current Drain:LESS THAN 25mA Modulation Type:FM RF Output:MORE THAN 13dBm Max Deviation:± 35KHz Spurious Emission:MORE THAN 55dB Dimensions:10.4x6.4x3.1 CM

HANDHELD	LAVALIER
 Receiver:KRV-202 Handheld Mic:KST-53V	 Receiver:KRV-202 Bodypack Transmitter:KLT-80V Lavalier Mic:LT-4A
HEADWORN	GUITAR/BASS
 Receiver:KRV-202 Bodypack Transmitter:KLT-80V Headworn Mic: HT-1A	 Receiver:KRV-202 Bodypack Transmitter:KLT-80V Guitar Cable:G-05
DUAL CHANNEL COMBO	
 Receiver:KRV-202 Handheld Mic:KST-53V Bodypack Transmitter:KLT-80V Lavalier Mic:LT-4A Headworn Mic: HT-1A Guitar Cable:G-05	